



Product	Name	Reg. no.	Category
	FTX Error Logger	211128A	SPEC
File Name	Type	Containing	
FTX-EL-INST-A	PROG	Error Logger Installer	
FTX-EL-ROUT-A	DATA	Error Logger Routing	
FTX-EL-ROUT-A	LIST	Error Logger Routing	
FTX-EL-PATCH-A	MAC	EL SINTRAN J patch	
FTX-EL-PATCH-A	MODE	EL SINTRAN J patchfile	
FTX-EL-LIB-1-A	BRF	EL-library 1bank	
FTX-EL-LIB-2-A	BRF	EL-library 2bank	
FTX-EL-LIB-5-A	NRF	EL-library ND500	
FTX-EL-LIB-A	IMPT	EL-library imports	
FTX-EL-MAN-A	PROG	Error Logger Manager	
FTX-EL-RT-A	PROG	Error Logger 'FTXEL'	
FTX-EL-WD-A	PROG	EL-Watch Dog 'FTXWD'	
UE-ERMSG-EN-C02	ERR	Error messages with FTX	
UELIB-P1-C	BRF	UE-library	
UELIB-D1-C	BRF	UE-library data	
UELIB-P2-C	BRF	UE-library	
UELIB-D2-C	BRF	UE-library data	
UELIB-P5-C	NRF	UE-library	
UELIB-D5-C	NRF	UE-library data	
UEER-CONVERT-C	PROG	Converts SECs to text	

## 1 NOTES

- <rev> is to be replaced by the current revision of the DIRECTORY or FILE.
- <lang> is to be replaced by the relevant language.
- The attached Software INFORMATION Reports should be read before installation.

## 2 The Product

This product consists of one part: FTX Error Logger.

## 3 Error-Logger Prerequisites

- In SINTRAN J, or later, one byte oriented internal device is required for internal error reporting and 250<sub>8</sub> words in resident used for patching.
- The two rt-programs, FTXEL and FTXWD, needs one segment each.

Product	Name	Reg. no.	Category
	FTX Error Logger	211128A	SPEC

#### 4 Installation procedure

For Error Logger on SINTRAN J, or later, the following apply:  
Installation is necessary after each load of SINTRAN from diskette.  
Conversely, load of SINTRAN is necessary before a second installation  
is attempted. This is also necessary if the installation fails after  
patching has started.

After a SINTRAN load, the installation may be run directly after the  
patchfile is finished, i.e. before the first cold start.

To perform the actual installation follow the steps below.

Always run this installation after load of SINTRAN from  
diskette on SINTRAN VSX/J or later.

- 1) Insert the first diskette (211128A-XX-01) into a floppy drive  
and enter the directory. Start the Error-logger installation  
program by

@(211128A-XX-01:FLOPPY-USER)FTX-EL-INST-A

and follow the instructions printed on the terminal.

- 2) Append the following line to the HENT-MODE file:

@MODE\_(FTX)FTX-EL-RT-A:LOAD

- 3) Append following lines to the LOAD-MODE file, after the point  
where XMSG is started:

@RT\_FTXEL  
@(FTX)FTX-EL-MAN-A  
START-ERROR-LOG,,  
EXIT  
@RT\_FTXWD

After the installation is finished, you must do a cold-start if using  
SINTRAN J or later.

Later installations may be started by activating the installation  
program residing on user FTX. Copying from diskette is only necessary  
when a new revision or version is received.